



ELECTRICAL DEMOLITION NOTES (This Drawing)

1. EQUIPMENT SHOWN TO BE REMOVED IS DIAGRAMMATIC AND DOES NOT REPRESENT THE FULL SCOPE OF DEMOLITION WORK. REMOVE ALL POWER, LIGHTING, FIRE ALARM, AND TELECOMMUNICATIONS DEVICES AND EQUIPMENT LOCATED WITHIN RENOVATION AREA UNLESS NOTED OTHERWISE. REMOVE WIRING BACK TO SOURCE OF SIGNAL AND/OR ORIENTATION. EXISTING TELECOMMUNICATIONS EQUIPMENT, INCLUDING TELECOMMUNICATION SWITCHES AND PATCH PANELS ARE TO BE REMOVED AND RELOCATED TO LOCATION SHOWN ON NEW WORK PLANS.
2. CONTRACTOR SHALL PROVIDE A MINIMUM TWO WEEKS WRITTEN NOTICE PRIOR TO ANY SHUT DOWN. NOTICE IS TO INCLUDE BUT IS NOT LIMITED TO THE LOCATION, PANELS, AND DURATION OF SHUT DOWN.
3. COTR SHALL HAVE RIGHT OF FIRST REFUSAL, TO ANY EQUIPMENT, DEVICES, LUMINAIRES, ETC. DEMOLISHED FROM THE RENOVATION AREA PRIOR TO DISPOSAL.
4. PROTECT THE EXISTING EQUIPMENT THAT IS TO REMAIN IN PLACE FROM DIRT, DUST, OR DAMAGE DURING THE COURSE OF DEMOLITION.
5. THE EXISTING FIRE ALARM CIRCUITS SERVING AREAS OUTSIDE OF THE SCOPE OF WORK SHALL REMAIN OPERATIONAL DURING THE ENTIRE DURATION OF THE CONSTRUCTION.
6. PROVIDE TEMPORARY SMOKE OR HEAT DETECTION ON THE FLOOR DURING THE ENTIRE DURATION OF CONSTRUCTION. SMOKE DETECTION SHALL BE PROTECTED FROM CONSTRUCTION DUST DURING WORKING. ONLY IN AREAS WHERE CONSTRUCTION WORK IS GOING TO BE OCCURRING.
7. REMOVE ALL LIGHTING FIXTURES, EXIT SIGNS, SWITCHES, CONTROL DEVICES, WIRING AND CONDUIT IN THE AREA OF DEMOLITION. REMOVE ALL WIRING BACK TO THE PANELBOARD IT ORIGINATES FROM.
8. REMOVE ALL RECEPTACLES, AND OTHER MISCELLANEOUS POWER CONNECTIONS TO EQUIPMENT IN THE AREA OF DEMOLITION SHOWN. REMOVE ALL CONDUIT AND WIRING BACK TO THE BRANCH PANELBOARD IT ORIGINATES FROM.

ELECTRICAL DEMOLITION NUMBERED NOTES (This Drawing)

- ① DISCONNECT AND REMOVE POWER TO THE AIR HANDLER. REMOVE CONDUIT AND WIRE BACK TO THE SOURCE.
- ② DISCONNECT AND REMOVE POWER TO THE EXHAUST FAN. REMOVE CONDUIT AND WIRE BACK TO THE SOURCE.
- ③ DISCONNECT AND REMOVE POWER TO THE PUMPS. REMOVE POWER BACK TO THE SOURCE.
- ④ DISCONNECT AND REMOVE PANELBOARD MCP-98 BACK TO SOURCE. ANY REMAINING LIVE CIRCUITS NOT SCHEDULED FOR DEMOLITION SHALL BE ROUTED TO NEW PANELBOARD L45A. REFER TO DRAWING EP03 FOR LOCATION OF PANELBOARD.
- ⑤ REMOVE LIGHTING IN THIS AREA BACK TO THE SOURCE.
- ⑥ REMOVE EXISTING PANELBOARD FEEDER BACK TO SOURCE, REFER TO DRAWING E500.
- ⑦ DISCONNECT AND REMOVE PANELBOARD BACK TO SOURCE.
- ⑧ REMOVE FEEDER TO FLOOR BELOW. PATCH FLOOR AS REQUIRED. MAINTAIN FIRE RATING OF EXISTING FLOOR ASSEMBLY.

## ELECTRICAL DEMOLITION LEGEND

ETR	EXISTING TO REMAIN
RR	REMOVE AND RELOCATE
RC	REMOVE COMPLETELY BACK TO SOURCE
RN	REMOVE AND REPLACE WITH NEW DEVICE, EXISTING CONDUIT, WIRING, AND BACKBOX SHALL BE REUSED

\_\_\_\_\_ EXISTING TO REMAIN  
 - - - - - TO BE DEMOLISHED

1 ELECTRICAL DEMOLITION PLAN - ATTIC FLOOR  
1/8" = 1'-0"

[illegible]